

B4200 SE

Output Power (RMS) @ .02% 1000Hz 14.4v Input
 4 Channels @ 40hms 111 Watts 50A
 4 Channels @ 20hms 205 Watts 100A
 4 Channels @ 10hm 200 Watts 116A
 2 Channels @ 80hms 223 Watts 50A
 2 Channels @ 40hms 411 Watts 101A
 2 Channels @ 20hms 400 Watts 124A

Frequency Response +/- 3db 4 Hz > 100kHz
 Crossover Range 30Hz - 550Hz (x10 300Hz - 5500Hz)
 Bass Boost 0 - 15db @ 20Hz-80Hz

S/N Ratio (A wtg) ref 1Watt 40hm >90 dB
 Seperation @ 1kHz >79 dB
 Damping (25W 4x40hm 100Hz) > 1200
 Low Level Input Sensitivity .3V - 4V
 Balanced Input Sensitivity .6V - 8V
 High Level Input NA
 Max Peak Current 20hm Stereo 222A @ 1800Watts 10% THD+N
 Efficiency >60%
 Idle Current 2.3A



